

耦合器



- 宽频带、高方向性、低损耗
- 承受功率最高可达1000W
- 单定向型、双定向型、大功率型、电桥式

■ 选型表

OH	系列号	S:单定向 D:双定向	接头	耦合度	频率
	1:小功率 2:大功率 3:电桥式		S:SMA F:母头 N:N 35:3.5mm K:2.92mm 24:2.4mm 185:1.85mm	例: 6:6dB	例: 0/0.6:DC~600MHz 0/6:DC~6GHz

■ 技术指标

型号	工作频率 (GHz)	耦合度 (dB)	耦合平坦度 (dB.max)	插损 (dB.max)	方向性 (dB.min)	驻波 (max)	功率 (W)	接口
OH1SSF10-1/12	1~12	10±1	±0.7	0.9	12	1.4	50	SMA-F
OH1SSF20-1/4	1~4	20±1	±0.7	0.4	20	1.2	50	SMA-F
OH1SSF30-0.5/6	0.5~6	30±1	±1	0.6	16	1.3	50	SMA-F
OH1SSF10-2/18	2~18	10±1	±1	0.8	15	1.5	50	SMA-F
OH1SSF20-2/18	2~18	20±1	±1	0.7	12	1.5	20	SMA-F
OH1SSF30-2/18	2~18	30±1	±1	0.7	12	1.5	20	SMA-F
OH1SKF10-0.5/26.5	0.5~26.5G	10±0.1	±1	2.1	12	1.5	20	2.92-F
OH1SKF20-0.5/40	0.5~40	20±1	±1.2	2.6	10	1.7	20	2.92-F
OK1SSF30-0.5/18	0.5~18	30±1	±1	1.2	10	1.4	30	SMA-F
OH1SKF10-1/40	1~40	10±1	±1.2	2.2	10	1.7	20	2.92-F
OH1SKF20-1/40	1~40	20±1	±1.2	2.0	10	1.7	20	2.92-F
OH1SKF30-1/40	1~40	30±1	±1.5	2.0	10	1.7	20	2.92-F
OH3SSF16-0.001/6	0.001~6	16±1	1	2.0	22	1.17	1	SMA-F
OH3SSF16-0.001/20	0.001~20	16±1.5	1.5	3.2	20	1.22	1	SMA-F
OH3SSF16-0.001/26.5	0.001~26.5	16±1.5	2	3.5	18	1.30	1	SMA-F
OH3S24F17-0.001/40	0.001~40	17±2	4	4.0	15	1.43	1	2.4-F
OH1DNF30-0.95/1.22	0.95~1.22	30±1	±1	0.3	20	1.25	100	N-F
OH1DSF20-0.5/18	0.5~18	20±1	±1	2.2	12	1.5	30	SMA-F
OH1DSF30-6/18	6~18	30±1	±1	0.9	15	1.5	30	SMA-F
OH1DSF20-0.5/3	0.5~3	20±1	±1	0.7	18	1.3	100	SMA-F
OH3DSF16-0.001/6	0.001~6	16±1	1	3.5	22	1.17	1	SMA-F
OH3DSF16-0.001/20	0.001~20	16±1	1.5	4.5	20	1.22	1	SMA-F
OH3DSF16-0.001/26.5	0.001~26.5	16±1	2	5.5	18	1.38	1	SMA-F
OH3D24F17-0.001/40	0.001~40	17±2	4	7.0	12	1.67	1	2.4-F